



5300 Beethoven Street, Los Angeles, CA 90066  
 TEL: (310)306-5556 • FAX: (310)821-7413  
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

**MODEL 5145**  
**0.7 - 3.0 GHz**  
**250 WATTS**  
**LINEAR POWER RF AMPLIFIER**

**Solid State  
 Broadband High  
 Power RF Amplifier**

The 5145 is a 250 Watt broadband amplifier that covers the 0.7 – 3.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability.

	Parameter	Specification @ 25° C
<b><u>Electrical</u></b>		
1	Frequency Range	0.7 – 3.0 GHz
2	Saturated Output Power	250 Watts min
4	Small Signal Gain	+54 dB min
5	Power Gain Flatness	+/- 3.0 dB maximum
6	IP <sub>3</sub>	+60 dBm typ.
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 100 Watts
9	Spurious Signals	< -60 dBc typical
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	2500 Watts max
12	AC Input	180 – 264 VAC, single phase
13	RF Input	+10 dBm max
15	Class of Operation	A/AB
<b><u>Mechanical</u></b>		
16	Dimensions	19" x 14" x 26" , (8U)
17	Weight	150 lb. max
18	Connectors	Type-N for RF In/Out
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<b><u>Environmental</u></b>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice

**ORDERING MODELS**

- ◇ RE - Rear panel RF connectors with IEEE-488, Ethernet and RS-232
- ◇ FE - Front panel RF connectors with IEEE-488, Ethernet and RS-232

**CIRCUIT PROTECTIONS**

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage
- ◇ VSWR protection
- ◇ RF Output over drive

**CIRCUIT INDICATIONS**

- ◇ Forward Power
- ◇ Reflected power
- ◇ VSWR Fault
- ◇ Temp Fault
- ◇ Gain Setting (VVA) percentage

**CIRCUIT CONTROL**

- ◇ Standby (amplifier disable)
- ◇ Gain/power setting with 25 dB range
- ◇ VSWR protection Reset
- ◇ ALC On/ Off