



5300 Beethoven Street, Los Angeles, CA 90066  
TEL: (310)306-5556 • FAX: (310)821-7413  
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 5155

**0.8 - 2.5 GHz  
250 WATTS  
LINEAR POWER RF AMPLIFIER**

### Solid State Broadband High Power RF Amplifier

The 5155 is a 250 Watt broadband amplifier that covers the 0.8 – 2.5 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability.

		Parameter	Specification @ 25° C
<b>Electrical</b>			
1	Frequency Range	0.8 – 2.5 GHz	
2	Saturated Output Power	250 Watts min	
3	Power Output @ 1dB Comp.	120 Watts min	
4	Small Signal Gain	+55 dB min	
5	Small Signal Gain Flatness	+/- 6 dB max with no ALC +/- 1 dB max with internal leveling	
6	IP <sub>3</sub>	+60 dBm typical	
7	Input VSWR	2:1 max	
8	Harmonics	-20 dBc typical @ 200 Watts	
9	Spurious Signals	> -60 dBc typical @ 250 Watts	
10	Input/Output Impedance	50 Ohms nominal	
11	AC Input Power	2800 Watts max	
12	AC Input	180 – 264 VAC, single phase	
13	RF Input	+10 dBm max	
14	RF Input Signal Format	CW/AM/FM/PM/Pulse	
15	Class of Operation	A/AB	
<b>Mechanical</b>			
16	Dimensions	19" x 14" x 26"	
17	Weight	150 lb. max	
18	Connectors	Type-N	
19	Grounding	Chassis	
20	Cooling	Internal Forced Air	
<b>Environmental</b>			
21	Operating Temperature	0° C to +50° C	
22	Operating Humidity	95% Non-condensing	
23	Operating Altitude	Up to 10,000' Above Sea Level	
24	Shock and Vibration	Normal Truck Transport	

### CIRCUIT PROTECTIONS

- ◊ Thermal Overload
- ◊ Over Current
- ◊ Over Voltage
- ◊ VSWR protection

### ORDERING MODELS

- ◊ RE            - Rear Panel model with RS232, IEEE, & with Ethernet Interface
- ◊ FE            - Front Panel model with RS232, IEEE, & with Ethernet Interface