

5300 Beethoven Street, Los Angeles, CA 90066 TEL: (310)306-5556 • FAX: (310)821-7413 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4034

400 - 450 MHz 250 WATTS LINEAR POWER RF AMPLIFIER

Solid State Band-specific High Power RF Amplifier

The 4034 is a 250 Watt band-specific amplifier that covers the 400 – 450 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 4034 comes with an extended multiyear warranty.

	<u>Parameter</u>	Specification @ 25 °C	
<u>Electrical</u>			
1	Frequency Range	400 – 450 MHz	
2	Saturated Output Power	250 Watts typical	
3	Power Output @ 1dB Comp.	150 Watts min	
5	Small Signal Gain +55 dB min		
6	Small Signal Gain Flatness	± 1.0 dB max	
7	IP ₃	+58 dBm typical	
8	Input VSWR	2:1 max	
9	Harmonics	-20 dBc typical @ 150 Watts	
10	Spurious Signals	> -60 dBc typical @ 150 Watts	
11	Input/Output Impedance	50 Ohms nominal	
12	AC Input Power	1200 Watts max	
13	AC Input	100 – 240 VAC, single phase	
14	RF Input	0 dBm max	
15	RF Input Signal Format	CW/AM/FM/PM/Pulse	
16	Class of Operation	AB	
<u>Mechanical</u>			
17	Dimensions	19" x 5.25" x 20"	
18	Weight	50 lb. max	
19	Connectors	Type-N	
20	Grounding	Chassis	
21	Cooling	Internal Forced Air	
<u>Environmental</u>			
22	Operating Temperature	0° C to +50° C	
23	Operating Humidity	95% Non-condensing	
24	Operating Altitude	Up to 10,000' Above Sea Level	
25	Shock and Vibration	Normal Truck Transport Specifications subject to change without notice.	

CIRCUIT PROTECTIONS

- ♦ Thermal Overload
- ♦ Over Current
- ♦ Over Voltage

ORDERING MODELS

- ♦ R Rear Panel Connectors
- ◊ F Front Panel Connectors
- ♦ RE R model w/Control Option
- ♦ FE F model w/Control Option
- ♦ RT RE model w/Ethernet Interface
- ♦ FT FE model w/Ethernet Interface



FE Model Shown

Approved By:	Date: