

5300 Beethoven Street, Los Angeles, CA 90066 TEL: (310)306-5556 • FAX: (310)821-7413 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4003

1.8 - 2.0 GHz **120 WATTS** LINEAR POWER RF AMPLIFIER

Solid State **Band-specific High Power RF Amplifier**

The 4003 is a 120 Watt band-specific amplifier that covers the 1.8 - 2.0GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 4003 comes with an extended multiyear warranty.


CIRCUIT PROTECTIONS

- ♦ Thermal Overload
- Over Current
- Over Voltage

ORDERING MODELS

- ¢ R - Rear Panel Connectors
- ♦ F - Front Panel Connectors
- RE R model w/Control Option
- ◊ FE F model w/Control Option
- ◊ FT FE model w/Ethernet Interface F Model Shown

	Parameter Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	1.8 – 2.0 GHz
2	Saturated Output Power	120 Watts typical
3	Power Output @ 1dB Comp.	100 Watts min
4	Small Signal Gain	+52 dB min
5	Small Signal Gain Flatness	<u>+</u> 0.75 dB max
6	IP ₃	+60 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 100 Watts
9	Spurious Signals	> -60 dBc typical @ 100 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	600 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	19" x 5.25" x 20"
17	Weight	48 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport
		Specifications subject to change without notice





Approved By:

Date: